


Firmware Update For WJ.00.0F

Because of several new features are included into the new version and some memory allocation is changed. Before you update, please kindly check your current P2000W's firmware version. **If your P2000W's current firmware version is earlier than WJ000C**, please kindly follow the firmware update procedure in below. And this action will clear your current settings to factory default.

1. Access the web page and select the "Update S/W" page.
2. In the Update Firmware option, set "**Ignore S/W Identify Function**" to **Yes** and click the submit button.
3. In the Update System option click the Browse button  to locate the new firmware file (**wj000f_img.ftp**). Click the Update button. Please note that the display of the Browse button depends on the language version of the Internet Explorer you are using.



The screenshot shows the web interface for the ZyXEL P2000W VoIP Wi-Fi Phone. The page has a purple header with the title "ZyXEL P2000W VoIP Wi-Fi Phone". Below the header is a green section titled "Update Firmware". In this section, there is a form with two fields: "TFTP IP Address" with the value "192.168.0.1" and "Ignore S/W Identify Function" with radio buttons for "No" and "Yes" (the "Yes" option is selected). Below these fields are "SUBMIT" and "CANCEL" buttons. Below the green section is a purple section titled "Update System". In this section, there is a "Select File" field with the value "C:\Documents and Settings\way" and a "Browse..." button. To the right of the "Select File" field is an "UPDATE" button. At the bottom of the page, there is a purple footer with a "RESTART" button on the left, a "SAVE" button on the right, and a navigation menu in the center containing links for "Information", "Network", "OutBound Proxy", "SIP Proxy", "Phone Book", "Wireless", "DSP Setting", "TOS/DS", "System", and "Update S/W".

4. Once the update has been completed, the P2000W phone will automatically reboot.
5. **Reset P2000W to factory default:** Press the two buttons at the same time and power on the phone. The LCD screen will display "Load Default Factory".

